

NP SERIES | INVERTER/CHARGER

24 VOLT PURE SINE WAVE POWER

Introduction

The NP Series inverter/charger provides choices to fit your specific mobile needs. There truly is a model that will work where you need it. The pure sine wave inverter is built to withstand high output surge demands of motors, pumps, and other tools, while providing high quality power for your sensitive electronic devices.



Features

- Battery Profile Presets – Using the included Seven Segment display or the optional remote LCD, easily choose from and set standard battery profiles, including Lithium Iron Phosphate (LFP), Gel, Flooded, and AGM.
- Wide operating temperature range from -40 °F to 149 °F.
- Programmable charger AC input current maximum with automatic load management regulation.
- Built-in AC bypass relay.
- Dead battery charging with a 0 volt minimum start.
- Thermally controlled cooling fan.
- GFCI outlet protection.
- LED indication of external power, inverter power, low input voltage, high temperature, and overload.
- Battery temperature sensor with 40 ft cable included with every unit.

Model Numbers

- 24NP36

Available For

- Marine Systems
- Military Vehicles
- RV Systems
- Trucks
- Utility Vehicles

Available Accessories

- LCD Remote
- Seven Segment Remote
- Battery Temp Sensor
- Battery Cable Kits
- DC Terminal Kits
- CAN Configuration Tools
- Covers
- GFCI



Pure Sine Wave



24 Battery Voltage Options



3600 W Continuous Output Options



SPECIFICATIONS



24NP36	
INVERTER SPECIFICATIONS	
Continuous power output at 25° C	3600 VA
Continuous current (amps AC)	30 AAC
Input current (amps DC)	Up to 167 ADC
Peak power (watts)	8000 W
Peak current (amps AC)	95 AAC
Motor starting rating (hp)	2 hp
Nominal AC output voltage	120 VAC ± 3%
Output frequency and accuracy	60 Hz ± 0.05%
Input battery voltage range	21 - 30 VDC
Inverter efficiency (peak)	88%
Total Harmonic Distortion (THD)	< 5%
Waveform	Pure Sine Wave
DC Input Capacitance	Up to 160,000uF
CHARGER SPECIFICATIONS	
AC input voltage range	95 - 135 VAC
Input current (amps AC)	25.2 AAC
Output (amps DC)	90 ADC
BYPASS SPECIFICATIONS	
Transfer relay (amps AC)	30 AAC
ENVIRONMENTAL SPECIFICATIONS	
Operating temperature	-40° C to +65° C (-40° F to 149° F)
PHYSICAL SPECIFICATIONS	
Dimensions (l x w x h)	14.8" x 17.1" x 8" (37.6 x 43.4 x 20.3 cm)
Weight	68 lb (30.9 kg)
GENERAL SPECIFICATIONS	
Listings	Listed to UL/cUL 458 UL File Number E100666
Warranty	Five years



GENERAL NOTES

Testing for specifications at 25° C.
Specifications subject to change without notice.



AGENCY APPROVALS & CERTIFICATIONS

- Listed to UL/cUL 458 UL File Number E100666

Sensata Technologies, Inc. ("Sensata") data sheets are solely intended to assist designers ("Buyers") who are developing systems that incorporate Sensata products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, evaluation and judgment in designing Buyer's systems and products. Sensata data sheets have been created using standard laboratory conditions and engineering practices. Sensata has not conducted any testing other than that specifically described in the published documentation for a particular data sheet. Sensata may make corrections, enhancements, improvements and other changes to its data sheets or components without notice.

Buyers are authorized to use Sensata data sheets with the Sensata component(s) identified in each particular data sheet. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER SENSATA INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN. SENSATA DATA SHEETS ARE PROVIDED "AS IS". SENSATA MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE DATA SHEETS OR USE OF THE DATA SHEETS, EXPRESS, IMPLIED OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. SENSATA DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO SENSATA DATA SHEETS OR USE THEREOF.

All products are sold subject to Sensata's terms and conditions of sale supplied at www.sensata.com SENSATA ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR THE DESIGN OF BUYERS' PRODUCTS. BUYER ACKNOWLEDGES AND AGREES THAT IT IS SOLELY RESPONSIBLE FOR COMPLIANCE WITH ALL LEGAL, REGULATORY AND SAFETY-RELATED REQUIREMENTS CONCERNING ITS PRODUCTS, AND ANY USE OF SENSATA COMPONENTS IN ITS APPLICATIONS, NOTWITHSTANDING ANY APPLICATIONS-RELATED INFORMATION OR SUPPORT THAT MAY BE PROVIDED BY SENSATA.

Mailing Address: Sensata Technologies, Inc., 529 Pleasant Street, Attleboro, MA 02703, USA.

CONTACT US

651-653-7000
800-553-6418
InverterInfo@sensata.com

Power Conversion
www.magnum-dimensions.com